



通过 WEB 界面在 EdgeSwitch 中开启 SSH/Https 详解

1. 通过 firefox 或 chrome 浏览器访问 ES24 默认管理 IP 地址


192.168.1.2






2. 选中主菜单 system 并点击 management access 分项




3. 选中 ssh 子菜单




4. 按图示生成 RSA Key 并确认证书状态为 present




5.按图示生成 DSA Key 且确认证书状态为 Present





6.确认 RSA/DSA KEY 状态都为 present 后,选择激活 ssh 模式




7.选择 save configuration 进行配置保存



8. 这里采用 Putty 通过 ssh 访问 ES24 管理 IP 地址 192.168.1.2





10. 同理开启 https

A screenshot of the EdgeMAX web interface, specifically the "Management Access > HTTPS" configuration page. The page title is "Secure HTTP Configuration". Under "HTTPS Admin Mode", the "Enable" radio button is selected. Other settings include "TLS Version 1" and "SSL Version 3" both enabled, "HTTPS Port" set to 443, "HTTPS Session Soft Time Out (Minutes)" set to 5, "HTTPS Session Hard Time Out (Hours)" set to 24, and "Maximum Number of HTTPS Sessions" set to 4. The "Certificate Status" field contains the word "Present" and has a red arrow pointing to it. At the bottom right of the form, there are "Submit", "Refresh", and "Cancel" buttons. A red arrow also points to the "Present" entry in the certificate status field.



优倍快网络技术咨询(上海)有限公司: www.ubnt.com.cn

优倍快网络技术论坛: <http://bbs.ubnt.com.cn>

Ubiquiti® community: <http://community.ubnt.com/>

Ubiquiti® Knowledge Base: <http://community.ubnt.com/t5/tkb/communitypage>

Ubiquiti® Training Academy: <http://www.ubnt.com/training/>